

# 40 Watts 2 channel Line Output Converter with Auto Remote Amplifier Turn-on | MHLCL12



Connect line output converter grey wire (+) and grey/black wire (-) to the right speaker output of the source unit

Connect line output converter white wire (+) and white/black wire (-) to the left speaker output of the source unit

Connect line output converter yellow wire to ACC + 12v

Connect line output converter black wire to ground

Connect line output converter blue wire to remote turn-on for amplifier

If there is only one stereo minus, connect both line output converters minus wires to it

The RCA jacks are the output for the line output converter, 6:1 step down w/adjust control pots for the desired output

